

Product datasheet

Specifications



APC Replacement Battery Cartridge 117 with 2 Year Warranty

APCRBC117

Overview

Lead Time Usually in Stock

Main

Product Or Component Type Replacement battery cartridge

Battery Type Lead-acid battery

Provided Equipment All required connectors
Battery recycling guide
Installation guide
Reusable packaging

Batteries & Runtime

Number Of Battery Blocks Per String 10

Number Of Battery Free Slots 0

Number Of Battery Filled Slots 0

Device Mounting Enclosed battery cartridge

Battery Voltage 120 V

Number Of Battery Replacement Quantity 1

Physical

Height 7.6 cm

Width 20.3 cm

Depth 58.4 cm

Net Weight 22.27 kg

Mounting Mode Not rack-mountable

Environmental

Ambient Air Temperature For Operation 0...40 °C

Operating Altitude 0...10000 ft

Relative Humidity 0...95 %

Ambient Air Temperature For Storage -15...45 °C

Storage Altitude 0.00...15240.00 m

Storage Relative Humidity 0...95 %

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Packing Units

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	22.8 cm
Package 1 Width	39.3 cm
Package 1 Length	76.1 cm
Package 1 Weight	25.18 kg
Scc14	731304282679

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Sustainability

Green Premium™ label is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

[Learn more >](#)



Take-back Transparency RoHS/REACH

Resource performance

 Take-Back Program Available

Certifications & Standards

Reach Regulation

[REACH Declaration](#)

Eu Rohs Directive

Pro-active compliance (Product out of EU RoHS legal scope)

[EU RoHS Declaration](#)

Environmental Disclosure

[Product Environmental Profile](#)

Circularity Profile

[End of Life Information](#)